

TMC SPECIFICATION

NO. S-1023

REV: A

COMPILED: JZ

CHECKED: JZ

APPD: *[Signature]*

SHEET 1 OF 10

TITLE:

Typed by mtp - 10/19/65

SBS-7 TEST PROCEDURE

TMC SPECIFICATION

NO. S - 1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 2 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mtp - 10/19/65

I. TEST EQUIPMENT REQUIRED

- A. One A-c VTVM Ballantine Model 314 (or equivalent).
- B. One RF VTVM Hewlett-Packard Model 410B (or equivalent).
- C. One RF generator - Measurements Corporation Model 82 (or equivalent).
- D. One audio generator - Hewlett-Packard Model 200 AB (or equivalent).
- E. One counter - Hewlett-Packard Model 523C (or equivalent).
- F. One audio analyzer - Panoramic Model LP-1A (or equivalent).
- G. One TTG (two tone generator) (or equivalent).
- H. One oscilloscope - Tektronix Model 515A (or equivalent).
- I. Two 600 ohm 1-watt resistors.

ADDITIONAL INFORMATION:

Supporting test specifications - S-628 Power supply
S-626 205 KC plug-in IF strip

II. PRELIMINARY

- A. Inspect the unit for mechanical imperfections such as loose screws, terminal boards, etc.
- B. Inspect for obvious wiring errors.
- C. Check for B+ shorts with an ohmmeter.
- D. Turn Power Switch to STAND-BY position, then plug unit into a-c outlet. The filament of the power supply tubes, V-7001 and V-7002, should be on. STAND-BY lights should go on immediately.
- E. Turn power switch from STAND-BY to ON. 60 seconds +20 seconds after applying a-c to the unit, the fan and B+ should be on. POWER ON light should go on immediately and STAND-BY light should go off.
- F. Check B+ on L6803 of A3627 terminal board. It should be +200 volts. Check B- on L-6805 of the same board. It should be -105 volts.

III. 205 KC OSCILLATOR

- A. Turn AFC switch to the OFF position. This in effect engages the 205 KC crystal oscillator.
- B. Turn the CHANNEL A DETECTION switch to the SSB position, and the CHANNEL B DETECTION switch to the AM position.
- C. Connect VTVM to Pin 2 of V-6203, and adjust R-6249 for a reading of -1 volt.
- D. Connect a counter to the output side (B1) of T-6204 (center conductor of coaxial cable is also on this point), and adjust C-6231 for 205,000 +1 cycle.
- E. Check back to Pin 2 of V-6203 as in C, and re-adjust R-6249 if necessary. The final setting should be of C-6231 for the proper frequency reading on the counter.

TMC SPECIFICATION

NO. S - 1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 3 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mp 10/19/65

III. 205 KC OSCILLATOR - Cont'd

- F. Connect a-c VTVM to the output of T-6204. It should be 1 volt +10%.
- G. With a-c VTVM still connected as in F, turn the CHANNEL A DETECTION switch from SSB to AM. The output should drop to 0 volts. Leave in the AM position.
- H. Turn the CHANNEL B DETECTION switch to the CW, then the SSB position. In both cases, the a-c VTVM should read 1 volt +10%.

IV. 705 KC OSCILLATOR

- A. With the AFC switch in the OFF position, the 705 KC crystal oscillator is activated.
- B. Connect VTVM to Pin 2 of V-6202, and adjust R-6215 for a reading of -1 volt.
- C. Connect a counter to the output side (B1) of T-6203 (center conductor of coaxial cable is also on this point), and adjust C-6214 for 705,000 +1 cycle.
- D. Check back to Pin 2 of V-6202 as in B, and re-adjust R-6215 if necessary. The final setting should be of C-6214 for the proper frequency.
- E. Connect a-c VTVM to the output of T-6213. It should be 1 volt +10%.

V. AGC COMPARITOR

- A. Turn the AGC SELECTOR switch to the CH-A-B position.
- B. Turn CHANNEL A & B AGC RESPONSE switches to the FAST position.
- C. Connect the VTVM to Pin 2, then Pin 7 of V-6206. A reading of 0 volts should exist in both cases.
- D. Rotate both pots R-6234 and R-6237 to the full clockwise position and place the VTVM on the slider arm of R-6234. Rotation of R-6234 should vary the d-c voltage from a positive to negative voltage from CW to CCW position. Repeat the same operation with R-6237.
- E. Adjust R-6234 to 0 d-c volts with the VTVM on the slider arm of this pot and lock.
- F. Place VTVM on the R-6237 slider arm. Adjust to 0 d-c volts and lock.

VI. MANUAL GAIN CONTROL

- A. Turn the AGC SELECTOR switch to the MANUAL position.
- B. Connect th VTVM at th junction of CR-6202 and CR-6203, and rotate th MANUAL GAIN control to the full clockwise position. The VTVM should read 0 volts.
- C. Rotation of the MANUAL GAIN CONTROL to th full CCW position should bring the voltage to -20 volts. Record the reading obtained on the Test Data Sheet.

TMC SPECIFICATION

NO. S-1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 4 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mtp 10/19/65

VII. CONVERTER AND 205 KC AMPLIFIER

- A. Set the RF generator for 205 KC and 10 MV output. Connect to J-6800, (the LoZ input), and the a-c VTVM on Pin 9 of V-6200. Rotate R-6813 to full CW position, AFC switch to ON and MANUAL GAIN control to maximum.
- B. Connect a temporary clip lead jumper across secondary of T-6200. This is to prevent inter-action of the secondary to the primary of T-6200.
- C. Tune the top slug on T-6200 for maximum indication.
- D. Remove jumper line connected in B, and adjust bottom slug for minimum indication on meter. Remove a-c VTVM and adjust RF generator output for 1 MV.
- E. Connect a-c VTVM to J-6804. Adjust slug on T-6201 for maximum indication on VTVM. Meter should read 7 MV or better. Record on Test Data Sheet.
- F. Connect VTVM to J-6801 Hi Z input. With 1 MV on J-6800, there should be 3 to 4 MV on J-6801.
- G. Place a-c VTVM probe on Pin 2 or 7 of V-6200. Rotation of R-6800 in the CCW direction should reduce the reading to 0 volts. Rotate R-6800 back to full clockwise position. Record voltage on Test Data Sheet.
- H. Converter and 205 KC Response:
 1. Set the RF generator for 500 KC and 1 MV output; AFC switch to OFF position.
 2. Connect a-c VTVM as in VII (E). Turn CHANNEL A DETECTION switch to SSB and CHANNEL B DETECTION switch to AM.
 3. Vary the frequency of the signal generator above and below 500 KC. Record the 3 db drop off points. Subtracting the two frequencies should give the overall bandpass of 20 KC \pm 1 KC.

VIII. IF AMPLIFIER OUTPUT

- A. The bandpass of the crystal filters may vary with the different customer orders. The 3.5 KC and 7.5 KC filters are more widely used and are illustrated in this procedure. The position of the filters in relation to USB and LSB may also vary with customer orders. In this procedure, the USB and LSB IF strips are plugged in as follows:

7.5 KC USB IF strip to J-6003
3.5 KC LSB IF strip to J-6000
3.5 KC USB IF strip to J-6002
7.5 KC LSB IF strip to J-6001

- B. Turn the AGC SELECTOR switch to the CH-A-B position.

TMC SPECIFICATION

NO. S-1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 5 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typ d by mtp 10/20/65

VIII. IF AMPLIFIER OUTPUT - Cont'd

- C. Turn CHANNEL A and B IF BANDWIDTH switches to the 7.5 KC position and connect a-c VTVM to J-102 of the 7.5 KC USB IF strip.
- D. Vary the RF generator approximately 1 KC below 500 KC and adjust for 10 MV output.
- E. The VTVM should show a peak of 1 volt. If this does not occur, set R-116 for 1 volt and remove VTVM.
- F. Turn CHANNEL A and B IF BANDWIDTH switches to the 3.5 KC position. Connect a-c VTVM to J-102 of the 3.5 KC USB IF strip and proceed as in Steps D and E.
- G. Turn CHANNEL A and B IF BANDWIDTH switches to the 3.5 KC position and connect a-c VTVM to J-102 of the 3.5 KC LSB strip.
- H. Vary the RF generator approximately 1 KC above 500 KC and proceed as in Step E.
- I. Turn CHANNEL A and B IF BANDWIDTH switches to the 7.5 KC position. Connect a-c VTVM to J-102 of the 7.5 KC LSB IF strip and proceed as in Steps E and H.

IX. AUDIO CHANNELS - A & B

- A. Connect one 600 ohm 1 watt resistor between terminals 7 and 9, and one between terminals 17 and 19 of E-6800. Turn CHANNEL A and B DETECTION switches to SSB. Adjust CHANNEL A and B LEVEL controls for 0 VU or 100% on the meters.
- B. Connect a-c VTVM between terminals 2 and 4 of E-6800 (CHANNEL A). It should read between 22 and 24 volts. Record on Test Data Sheet.
- C. Connect a-c VTVM between terminals 12 and 14 of E-6800 (CHANNEL B). It should read between 22 and 24 volts. Record on Test Data Sheet.
- D. Remove RF generator from J-6800. Set IF BANDWIDTH switches A and B to OFF position, (OFF is midway between any two bandwidth positions). Switch to a-c VTVM to a low range, and adjust R-6073 (CHANNEL B hum balance control) for minimum reading. It should read 230 MV or less. Record on Test Data Sheet. Turn CHANNEL B DETECTION switch to AM. The VTVM should read approximately 23 MV. Record on Test Data Sheet. Turn CHANNEL B DETECTION switch to SSB position.
- E. Connect a-c VTVM between terminals 2 and 4 of E-6800 and adjust R-6036 (CHANNEL A hum balance control) for minimum reading. It should read 230 MV or less. Record on Test Data Sheet. Turn CHANNEL A DETECTION switch to AM. The VTVM should read approximately 23 MV. Record on Test Data Sheet. Turn CHANNEL A DETECTION switch to SSB position.

TMC SPECIFICATION

NO. S - 1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 6 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mtp 10/20/65

IX. AUDIO CHANNELS - A & B - Cont'd

- F. Connect audio generator on the post of R-6005, (15 K resistor to 5814 grid), and set frequency at 1 KC and 2.5 MV output. Adjust CHANNEL A and B LEVEL controls for 0 VU or 100% on the meters. Connect scope between terminals 2 and 4 of E-6800. Set AFC switch to ON position.
- G. Vary the audio generator above and below 1 KC. The 3 db points should be 200 cycles or lower and 10 KC or higher. A clean sine wave should appear on the scope. Record on Test Data Sheet.
- H. Connect a-c VTVM and scope between terminals 12 and 14 of E-6800 (CHANNEL B) and repeat Step G.
- I. Replace audio generator with TTG. Set controls as follows:
1. POWER switch to ON.
 2. RF TONE SELECTOR to OFF.
 3. AUDIO TONE SELECTOR to TWO TONE.
 4. AUDIO OUTPUT control for 2.5 MV output.
- J. Adjust CHANNEL A and B LEVEL controls for 0 UV or 100% on the meters.
- K. Connect audio analyzer between terminals 2 and 4 of E-6800 (CHANNEL A). Set controls as follows:
1. POWER switch ON.
 2. VERT. CALIB. SELECTOR to DB.
 3. SWEEP RANGE SELECTOR to 20 KC LOG.
 4. SCALE SELECTOR to 0.5.
 5. INPUT MULT. to X1 K.
 6. INPUT POT. - Set the control so that the top of the two tones is on the +20 DB line of the screen. The total distortion products should be 40 db down. Record on Test Data Sheet.
- L. Connect audio analyzer between terminals 12 and 14 of E-6800 (CHANNEL B) and repeat Step K-6. Remove TTG and audio analyzer. Set AFC switch to OFF position.

X. PHONE MONITOR

- A. Connect RF generator to J-6800. Connect earphones to MONITOR jack. Adjust CHANNEL A and B LEVEL controls for 0 VU or 100% on the meters.
- B. A 1 KC tone should be heard on the phones, in the full CW and full CCW position of the MONITOR control.

TMC SPECIFICATION

No. S-1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 7 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mtp 10/20/65

X. PHONE MONITOR - Cont'd

- C. Turn CHANNEL A IF BANDWIDTH switch to 7.5 KC LSB and rotate MONITOR control to full CW position. The 1 KC tone should be heard on the phones.
- D. Connect a-c VTVM to J-6202 MONITOR jack. It should read 2 volts +20%. Record on Test Data Sheet at full CW & CCW position.

XI. PRODUCT DETECTORS

- A. Connect a-c VTVM to the post of R-6005. There should be 1 volt +10% at 205 KC on this post. Record on Test Data Sheet.
- B. Connect RF generator to the post of R-6082. Set generator for 204 KC and .33 volts output.
- C. Adjust LINE LEVEL control on CHANNEL A for 0 VU or 100% on meter. Connect a-c VTVM and scope to terminals 2 and 4 of E-6800. The VTVM should read between 22 and 25 volts, and there should be a clean sine wave on the scope. Record on Test Data Sheet.
- D. Connect RF generator to the post of R-6083.
- E. Adjust LINE LEVEL control on CHANNEL B for 0 VU or 100% on meter. Connect a-c VTVM and scope to terminals 12 and 14 of E-6800. The VTVM should read between 22 and 24 volts and there should be a clean sine wave on the scope. Record on Test Data Sheet.

XII. AM DETECTORS

- A. Turn CHANNEL A and B DETECTION switches to AM.
- B. Adjust RF generator for 205 KC with a 1 KC 50% modulation and .33 volts output.
- C. Connect RF generator to Pin 3 of T-6002 on detector board A-3641. Adjust CHANNEL B LINE LEVEL control fro 0 VU or 100% on meters. The VTVM should read between 22 and 24 volts, and there should be a clean sine wave on the scope. Record on Test Data Sheet.
- D. Connect a-c VTVM and scope to terminals 2 and 4 of E-6800.
- E. Connect RF generator to Pin 3 of T-6000 on detector board A-3640. Adjust CHANNEL A LINE LEVEL control for 0 VU 100% on meter. The VTVM should read between 22 and 24 volts, and there should be a clean sine wave on the scope. Record on Test Data Sheet.

XIII. AGC RESPONSE

- A. Connect RF generator to J-6800 at 500 KC and 1 MV out.
- B. Set CHANNEL A to 7.5 KC and CHANNEL B to 7.5 KC.

TMC SPECIFICATION

No. s- 1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 8 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mtp 10/20/65

XIII. AGC RESPONSE - Cont'd

- C. Vary generator 1 KC below 500 KC. Set CHANNEL B LINE LEVEL for 0 VU.
- D. Set AGC selector MANUAL.
- E. Turn MANUAL GAIN control to full CCW position. The output drops to 0.
- F. Turn control to full CW position. The output should rise immediately.
- G. Set AGC RESPONSE to MED position.
- H. Turn MANUAL GAIN control full CCW, then back to CW. The output should hesitate before rising.
- I. Set AGC RESPONSE to SLOW position.
- J. Turn MANUAL GAIN control full CCW, then back to CW. The output should rise very slowly.
- K. Vary RF generator 1 KC above 500 KC. Set CHANNEL A LINE LEVEL for 0 VU.
- L. Repeat Steps E to J for CHANNEL.

XIV. IF AMPLIFIER BANDWIDTH CHECK

- A. Connect RF generator to J6800 at 500 kc and 1 MV out.
- B. Connect 600 ohm load to terminals 7 and 9 of E6800.
- C. Connect VTVM and Frequency Counter to terminals 2 and 4 of E6800.
- D. Set Ch A & B to 7.5KC. Detection to SSB, AFC "OFF" and AGC tp CH A/B.
- E. Ground AGC to IF strip at R119 on strip terminal board.
- F. Tune generator around 500KC for output indication on VTVM.
- G. Set Ch A line level for reference DB around 22 V output. (0VU on SBS meter)
- H. Sweep generator through IF bandwidth, checking 3DB points.
- I. Minimum Bandwidth of IF should be as indicated on strip (i.e. - 7.5 LSB/BW=7500 cps MIN)
- J. Repeat Steps E to I for each IF strip. Record results.

XV. Repeat Step III. Record oscillator volts and frequency on Test Data Sheet.

Repeat Step IV. Record oscillator volts and frequency on Test Data Sheet.

TMC SPECIFICATION

NO. S-1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 9 OF 10

TITLE: SBS-7 TEST PROCEDURE

Typed by mtp 10/20/65

THE TECHNICAL MATERIEL CORPORATION
MAMARONECK, N.Y.SBS-7 TEST DATA SHEET #1

SERIAL NO.: _____

MFG. NO.: _____

AGC COMPARATOR

BALANCE POTENTIOMETER _____ OK

MANUAL GAIN CONTROLAGC _____ VOLTS
AGC POTENTIOMETER _____ OK205 KC CONVERTER AND AMPLIFIER205 KC AMPLIFIER OUTPUT _____ VOLTS
Lo Z INPUT AND INPUT POTENTIOMETER _____ OK
Hi Z INPUT _____ VOLTS
RESPONSE: 3DB POINTS _____ KC AND _____ KC
BANDPASS _____ KCIF AMPLIFIER BANDWIDTH TEST7.5 LSB _____ OK
3.5 LSB _____ OK
3.5 USB _____ OK
7.5 USB _____ OKAUDIO OUTPUTCHANNEL A _____ VOLTS
CHANNEL B _____ VOLTSHUM BALANCECHANNEL A SSB _____ MV AM _____ MV
CHANNEL B _____ MV _____ MV

TMC SPECIFICATION

NO. S-1023

REV: A

COMPILED: JZ

CHECKED:

APPD:

SHEET 10 OF 10

TITLE: SBS-7 TEST PROCEDURE

Type d by mtp 10/20/65

TEST DATA SHEET #2

AUDIO FREQUENCY RESPONSE (3DB POINTS)

CHANNEL A _____ CYCLES AND _____ KC
CHANNEL A WAVESHAVE _____ OK
CHANNEL B _____ CYCLES AND _____ KC
CHANNEL B WAVESHAVE _____ OK

AUDIO DISTORTION

CHANNEL A _____ DB
CHANNEL B _____ DB

PHONE MONITOR OUTPUT

CW CONTROL _____ VOLTS
CCW CONTROL _____ VOLTS

PRODUCT DETECTORS

205 KC PRODUCT DETECTION INJECTION _____ VOLTS
CHANNEL A _____ OK
CHANNEL B _____ OK

AM DETECTORS

CHANNEL A _____ OK
CHANNEL B _____ OK

AGC RESPONSE

CHANNEL A _____ OK
CHANNEL B _____ OK

205 KC OSCILLATOR

OSCILLATOR _____ VOLTS.
OSCILLATOR FREQUENCY _____ CYCLES.

705 KC OSCILLATOR

OSCILLATOR _____ VOLTS
OSCILLATOR FREQUENCY _____ CYCLES

DATE: _____

TESTER: _____

